CABLINE®-VS

VESA standard connector, Suitable for high-data-rate transfer (20 Gbps/lane), Mechanical locking bar, 0.5 mm pitch, Horizontal mating type micro-coaxial connector

Product Specifications:

Mating type		Horizontal
Board Pitch (mm)		0.5
Wiping Length (mm)		0.61
Mated size (mm)	Height	1.0 +/- 0.1
	Width	Formula: 7.55 + (0.5*?p)
	Depth	5.8
Pin Counts	Range	Up to 50
	Available	20, 30, 40, 50

^{*} Please inquire for pin counts not listed or outside of the pin count range.

Applicable Cable Size:

Maximum O.D. (mm)	0.5	
Micro-Coaxial	45 ohm: #36 or smaller	
for Signal (AWG)	50 ohm: #38 or smaller	
Twinax (AWG)	#40	
Discrete (AWG)	#32 or smaller	

Applicable Standards (Reference Only):

USB4 Gen3 /Thunderbolt 4 (20 Gbps/lane), PCIe (16 GT/s), eDP (8.1 Gbps)



High-Data-Rate Transfer, Ideal for USB4 Gen3/Thunderbolt 4 (20 Gbps/lane) Applications


USB4 Gen3/Thunderbolt 4 (20 Gbps/lane)

Eye pattern (Differential)


Bit rate: 20 Gbps

Rise time: 30ps (10-90%) Input voltage: 800mVp-p

details.



Mechanical Locking Bar Prevents Incomplete Mating and Back-out/Un-mating




Multiple Connector Options with I-PEX VS Series

I-PEX VS series (0.5 mm pitch, horizontal mating type)

CABLINE-VS, VS II receptacles and EVAFLEX® 5-VS can be mounted to the same PCB layout.

CABLINE-VS Receptacle:


Has #1 share in the Notebook PC panel connector market as VESA standard connector.




^{*}Please contact I-PEX Connectors for more test

Component Parts Details

Component Parts








Plug for Cable Assembly

2.PULL-TAPE CAN BE PUT WITHIN THE RANGE OF "H"(STRAIGHT AREA)

3.SOLDERING IS ONLY A CASE WITH GND-BAR




Recommended P/N 20453-2**T-03(20P/30P/40P)	20453-250T-03S(50P)	
PART NO. Pos. A B C D 20453-#20T-#2 20 9.50 10.30 12.56 16.00	T PULL-BAR	Halogen Free RoHS Complian
TOP VIEW D ±0.15 SOLDERING SEE NOTE.3 CA A ±0.1	ABLE 2 CONTACT BO THOUSING 4 SHELL-B SECT X-X S= 10:1	NDING MATING LENGTH
C	<u>↓</u>	PLUG P/N: 20453-#**T-#2#
BOTTOM VIEW	0.76	
SOLDERING.		PART NO. CABLE ASS'Y HOUSING ASS'Y SHELL-A PULL-BAR PART NO. PART
ප ිව <u>ந்தைகைகள்கள்களைகளைக</u>் சடி ප		






Plug for Cable Assembly




PART NO. Pos. 20453-#20T-## 20 9.50 30 14.50 20453-#30T-## 0.50 ±0.1 19.50 20453-#40T-## 50 24.50 20453-#50T-##S CENTER CONDUCTOR INSULATOR **OUTER CONDUCTOR** Øa +0.05 a -0.02 CUT LINE (AFTER SOLDERING COAT) GND-BAR . Ø 0.30 MAX. MICRO-COAXIAL CABLE DIMENSION 0.51 +0.07 3 Ø 0.5 MAX. 1.70 ±005 0.10 ±0.1 #36 0.15 #38 0.12 #40 0.09 **JACKET** #44 0.063 A+1.2 ±0.1 MICRO-COAXIAL CABLE AWG#** RECOMMENDED MICRO-COAXIAL CABLE DIMENSION A ±0.1 A ±0.1 0.50 ±0.1 . 0.50 ±0.10 CENTER CONDUCTOR CENTER CONDUCTOR INSULATOR Ø 0.09 +0.05 -0.02 **CUT LINE** (AFTER SOLDERING COAT) OUTER CONDUCTOR (AFTER **CUT LINE** SOLDERING COAT) GND-BAR Ø0.5 MAX. Ø0.21 DISCRETE WIRE DIMENTION 0.51 +0.07 #32 0.24 #34 0.192 0.40 #36 0.15 0.60 JACKET, JACKET DISCRETE WIRE AWG#** . 1.00 ±0.1 TWINAX CABLE AWG#40 RECOMMENDED DISCRETE WIRE DIMENSION RECOMMENDED TWINAX CABLE DIMENSION




Plug for Cable Assembly





Rev.34

Plug Housing Assembly




NOTES.

1.THIS PART IS ASSEMBLED WITH SHELL-A(P/N:2574-#**) AFTER SOLDERED THE CABLE, AND IT BECOMES P/N:20453-#**T-#**. THIS PART IS ASSEMBLED WITH SHELL-A type-H(P/N:2699-#40) AFTER SOLDERED THE CABLE, AND IT BECOMES P/N:20508-040T-#*. THIS PART IS ASSEMBLED WITH SHELL-A(P/N:2574-#**) AND ALIGNMENT COVER(P/N:2658-0**) AFTER SOLDERED THE CABLE, AND IT BECOMES P/N:20492-1**T.




Plug Housing Assembly




Rev.20

Pull Bar






Shell-A




Rev.15

Receptacle Assembly






Receptacle Assembly



Rev.31




NOTES.


IN CASE OF PLUG WITH PULL-BAR, DO NOT MOUNT ANOTHER COMPONENT IN THIS AREA.
 SOLDER RESIST MUST BE APPLIED TO THIS AREA.




Receptacle Assembly



CONNECTOR ON RECOMMENDED FOOTPRINT PATTERN P/N: 20455-0**E-##



CONNECTOR ON RECOMMENDED FOOTPRINT PATTERN
P/N: 20455-A20E-##



Rev.31

ITEMS	SPECIFICATION		
APPLICABLE CABLE	MICRO-COAXIAL CABLE : AWG# 44, 42, 40, 38, 36 DISCRETE WIRE : AWG# 36, 34, 32 TWINAX CABLE : AWG# 40		
RATING VOLTAGE	100V AC (PER CONTACT PIN)		
RATING AMPERAGE (FOR CONTACT)	0.1A AC/DC [AWG#44] PER CONTACT PIN/UP TO 50 CONTACTS 0.24A AC/DC [AWG#42] PER CONTACT PIN/UP TO 50 CONTACTS 0.3A AC/DC [AWG#40] PER CONTACT PIN/UP TO 50 CONTACTS 0.5A AC/DC [AWG#38] PER CONTACT PIN/UP TO 14 CONTACTS 0.8A AC/DC [AWG#36] PER CONTACT PIN/UP TO 10 CONTACTS 1.0A AC/DC [AWG#34] PER CONTACT PIN/UP TO 6 CONTACTS 1.0A AC/DC [AWG#32] PER CONTACT PIN/UP TO 6 CONTACTS TESTING BY A REAL MACHINE IS RECOMMENDED BECAUSE TEMPURECHER RISE MAY AFECTED BY ACTUAL SITUATION.		
OPERATING TEMPERATURE	233~358K(-40°C~+85°C)		
OPERATING HUMIDITY	85% R.H. MAX.(NON-CONDENSING)		
CONTACT RESISTANCE	INITIAL: 140mohm MAX.(AWG#32) / AFTER TEST: △40mohm MAX. 180mohm MAX.(AWG#34) 275mohm MAX.(AWG#36) 360mohm MAX.(AWG#38) 600mohm MAX.(AWG#40) 700mohm MAX.(AWG#42) 1080mohm MAX.(AWG#44)		
GROUND SHELL RESISTANCE	INITIAL: 50mohm MAX. / AFTER TEST: ∠40mohm MAX.		
INSULATION RESISTANCE	INITIAL: 1000Mohm MIN. / AFTER TEST: 500Mohm MIN.		
DIELECTRIC WITHSTANDING VOLTAGE	AC250V 1min		
DURABILITY	30 CYCLES		
MATING FORCE (INITIAL / AFTER TEST)	20P : 9.45N MAX. 30P : 12.15N MAX. 40P : 16.20N MAX. 50P : 20.25N MAX.		
UNMATING FORCE (INITIAL / AFTER TEST)	20P : 2.0N MIN. 30P : 3.0N MIN. 40P : 4.0N MIN. 50P : 5.0N MIN.		
CABLE RETENTION FORCE	20P : 9.80N MIN. 30P : 14.70N MIN. 40P : 19.60N MIN. 50P : 24.50N MIN.		
COPLANARITY	0.10 MAX.		
PRODUCT SPECIFICATION	PRS-1427		
TEST REPORT	TR-08047 (20455-#**E-#2) TR-13084 (20455-#**E-#6, 20455-0**E-#8)		
PACKING STANDARD	300-643		
NSTRUCTION MANUAL	HIM-08004		
APPEARANCE CRITERIA NO.	QLS-A***		

I-PEX



IASLP, ESTORQ, ISFIT, i-Fit and ZenShield are registered trademarks of I-PEX Inc. Please note that the contents in the catalog might be changed without prior notification. I-PEX Inc. assumes no responsibility for any inaccuracies or obligation to update Information on these documents. Please be sure to read and understand the latest "Precautions for Use" and "Instruction Manual" before you use our products. We shall not be responsible for any defects, damages or troubles in case you use our products without following the precautions for use. Please feel free to contact our sales representatives when you use our products for any applications that require very high reliability and safety, or that relate to human life (ex. nuclear power control, aerospace, transportation, medical equipment, safety equipment etc.).

Contact your sales representative or more detailed information.

www.i-pex.com

