

M series

Proportional resistive fingertip controllers • potentiometer technology



DISTINCTIVE FEATURES

- One, two or three axis
- Analog output
- Low profile mounting depth
- Friction centering option
- Low profile design with multiple handle options



ENVIRONMENTAL SPECIFICATIONS

- Operating Temperature: -25 °C to +70 °C (-13 °F to +158 °F)
- Storage Temperature: -40 °C to +70 °C (-40 °F to +158 °F)



MECHANICAL SPECIFICATIONS (X & Y AXIS)

- Operating Force: 1.3 N (0.29 lbf)
- Maximum Vertical Load: 100 N (22.5 lbf)
- Maximum Horizontal Load: 100 N (22.5 lbf)
- Mechanical Angle of Movement: 56°
- Expected Life: See potentiometer options
- Mass/weight: Varies
- Lever Action (centering): Spring or friction



MECHANICAL SPECIFICATIONS (Z AXIS)

- Operating Torque: 0.040 Nm (0.35 lbf in)
- Break out Torque: 0.022 Nm (0.19 lbf in)
- Maximum Allowable Torque: 0.049 Nm (0.43 lbf in)
- Mechanical Angle of Movement: 90°
- Lever Action (centering): Spring



MATERIALS

- Body: Nylon
- Actuator: Nylon

The company reserves the right to change specifications without notice.



M series

Proportional resistive fingertip controllers • potentiometer technology




WIRING DIAGRAM

DEFAULT WIRE COLOR CODE *		
COLOR	FUNCTION	AWG
2 OR 3 AXIS JOYSTICK WITH 1 PUSHBUTTON: OPTIONS 5, E, G, H, 9, N		
Orange	Switch 1	28
Orange	Switch Common	
3 AXIS JOYSTICK WITH 2 PUSHBUTTONS: OPTION Q**		
Orange	Switch 1	28
Brown	Switch 2	
Green	Switch Common	
Z AXIS IN A 3 AXIS JOYSTICK: OPTION 8, 9, M, N, Q		
Red	Supply	28
White	Signal	
Blue	Return	

* Wires for the Z axis and the pushbuttons are 292 mm (11.5in) and stripped

** Handle Q pushbuttons are shown in the following drawing



OUTPUTS


POTENTIOMETER OPTIONS

POTENTIOMETER	P	R
Electrical Element	CONDUCTIVE PLASTIC	
Track Resistance	5K	
Linearity	±1.0%	±1.0%
Track Operating Angle	220°	50°
CRV	±1.5%	±1.0%
Power Dissipation	0.25W@40 °C	1 W
Rotational Life	1,000,000	10,000,000



MOUNTING

INSTALLATION



FRONT MOUNTING BEZEL (FM)



C = Split Bezel

Cutout dimensions = 39.70 mm (1.562 in)



L = Rubber Boot

Cutout dimensions = 39.70 mm (1.562 in)

REAR MOUNTING BEZEL (RM)



F = Square Bezel

Cutout dimensions = 30.15 mm (1.187 in)

MOUNTING ACCESSORIES

Standard hardware includes:

C=Ring, cup and 4 black Phl screws 2-56x 1/2 in

L=Ring and 4 black Phl screws 2-56x 1/2 in

F=Square bezel, 4 screws 2-56x1/2 in Phl and 4 screws 2-56x 1/2 in Phl

Proportional resistive fingertip controllers • potentiometer technology





BUILD YOUR PART NUMBER

SERIES	MODEL	MOUNTING BEZEL	CENTERING	HANDLE	OUTPUT OPTIONS POTENTIOMETERS
M	1				
	1 2 Axis	C Split Bezel	0 Spring Centering	Model 1: 2 axis handles	P 5KΩ, 220°
	2 2 Axis with pushbuttons	F Square Bezel	6 Torque Set (Friction)	0 Tapered Convex	R 5KΩ, 50°
	3 3 Axis	L Rubber Boot Kit		1 Concave Tip	
	4 3 Axis with pushbuttons			2 Flat Tip	
				3 Concave Tip - long	
				6 Straight tip - short	
				A Straight tip - mid	
				B Straight tip - long	
				C Ball tip	
				Model 2: 2 axis handles with pushbuttons	
				5 Pushbutton	
				E Pushbutton	
				G Pushbutton	
				H Pushbutton	
				Model 3: Three axis	
				8 3 axis	
				M 3 axis	
				Model 4: Three axis with pushbuttons	
				9 3 axis with 1 pushbutton	
				N 3 axis with 1 pushbutton	
				Q 3 axis with 2 pushbuttons	

M series

Proportional resistive fingertip controllers • potentiometer technology

2 AXIS - OPTION A HANDLE




Mechanical dimensions represent a joystick with the largest potentiometer option. Potentiometer size will vary according to selected option




HANDLE OPTIONS

TWO AXIS




TWO AXIS WITH PUSHBUTTONS




M series

Proportional resistive fingertip controllers • potentiometer technology

THREE AXIS




8




M


THREE AXIS WITH PUSHBUTTONS



9



N



Q